

INDUCTIVE POWER SOURCE FOR PERIPHERAL DEVICES

5 TECHNICAL FIELD

This disclosure relates to inductively providing a power source to peripheral devices, and, more particularly, to a system for inductively providing power to peripheral devices during the normal use of the peripheral device.

10 BACKGROUND

15 Devices peripheral to personal computers are used for a variety of input or output purposes. Computer input devices include keyboards, mice, drawing tablets, cameras, *etc.*, while computer output devices include speakers, printers, monitors, *etc.* Almost without exception, peripheral devices require a power source for proper operation. Oftentimes the power source comes from a standard cable coupling the peripheral device to the computer, such as connection cables for using Universal Serial Bus (USB, developed by the USB Implementers Forum, Inc.), PS/2 (International Business Machine's Personal System 2), RS232 (now renamed to EIA232 of the Electronic Industries Association), FireWire
20 (Institute of Electrical and Electronics Engineers, Inc.'s 1394-1995 standard), *etc.* These cables typically provide a 5-volt dc voltage at a given current capacity to drive the device. Computer mice, for example, are typically powered at ~ 500 mA, to power the various internal circuits within them that track their movement and communicate the status of their mechanical buttons to their host
25 computer.

Because a mouse cord can be cumbersome and unwieldy, there is a consumer demand for cordless mice. Thus, a new generation of mice have been

developed that communicate their signals to their host computer via "wireless" signals, such as infrared (IR), radio frequency (RF), or ultrasonic signals. These wireless mice generally contain their own power source, because including a cord only to supply power to the mouse defeats the purpose of making the signal communication wireless.

The typical solution to self-powering a mouse is to include batteries within the mouse itself. Normally, high-energy batteries such as alkaline batteries are used so that they can provide power for a relatively long time between battery changes. In order to reduce overall power consumption, power saving features are implemented into wireless mice to extend the life of the batteries. For example many wireless mice will automatically "power down" their circuitry after a period of inactivity. Such power savings features can allow wireless mice to operate for months before requiring new batteries.

As new features are added to mice, such as adding a wheel for easy document scrolling, their circuitry becomes more complex. Complex circuitry, in turn, generally requires higher power requirements. These power requirements include not only how much power is needed over time, *i.e.*, how long can a user go before the batteries cannot power any of the mouse circuitry, but also include a peak power requirement, *i.e.*, how much instantaneous power is required to supply a specific circuit in the mouse. Particular circuits such as optical mouse tracking or radio module operations may require relatively high peak energy from the batteries for proper operation.

Although rechargeable batteries generate less power than alkaline batteries, they can be recharged hundreds or thousands of times, and thus provide power at a relatively low lifetime cost. Some computer peripheral products include a "docking cradle" or other place to rest the product during periods of non-operation, and some of the docking cradles include a battery re-

charger to automatically recharge batteries in the device while it is in its docking
cradle. This is typically done by exposing small electrodes within the docking
cradle that transfer power to a matching set of electrodes on the device. Within
the device, a circuit transfers the power that is applied to the electrodes directly
5 to the batteries, thereby recharging them.

Requiring a device to be placed in a docking cradle to recharge its
batteries means that it cannot be used while recharging. Also, if a user forgets to
recharge the batteries for a period of time and they discharge, the user cannot
operate the device until the batteries are again recharged. Most likely a user
will discover that the batteries are discharged at a time the device is needed.
10 Adding small wires that could recharge the batteries during device operation
would defeat the purpose of having a wireless device.

Embodiments of the invention address these and other deficiencies in the
prior art.

BRIEF DESCRIPTION OF THE DRAWINGS .

The description may be best understood by reading the disclosure with
reference to the drawings, wherein:

FIG. 1 is a perspective view of an inductive power supply system according
20 to an embodiment of the invention.

FIG. 2 is a cross sectional view of a mouse and mousepad containing an
inductive charging system according to an embodiment of the invention.

FIG. 3 is a cross sectional view of a mouse and mousepad containing an
inductive charging system according to another embodiment of the invention.

FIG. 4 is a functional block diagram showing connections and circuit
25 blocks used in the inductive charging system according to embodiments of the
invention.

FIG 5 is a perspective view of a docking cradle adapted to include an inductive charging system according to an embodiment of the invention.

FIGs. 6A and 6B are top view diagrams showing example layouts of the source loop in relation to the mousepad for embodiments of the invention.

FIG. 7 is a top view diagram showing an example layout of the victim loop in relation to the mouse for embodiments of the invention.

FIG. 8 is a cross sectional diagram of a mousepad showing a further example of an embodiment of the invention.

DETAILED DESCRIPTION.

Embodiments of the invention include a base and peripheral device combination that can inductively provide power to a peripheral device. The power supplied to the peripheral device could drive the device directly, or could be used to charge an energy supply, such as batteries contained within the device. An example of such a system is a mousepad base and a mouse containing rechargeable batteries.

Coils or loops of wire are present in both the mousepad and in the mouse. The coils in the mousepad are energized to create a constantly changing magnetic field. When the coils in the mouse are exposed to the changing magnetic field made by the mousepad, an induced voltage and a current flows in the coils of the mouse. The induced current and voltage provide enough energy to partially or completely recharge batteries in the mouse and, as power requirements of the mouse decrease, may be able to provide enough energy to power the mouse directly without using the power reserve of the batteries.

FIG. 1 is a perspective view of an inductive re-charger system 10, which includes a mousepad 20 and a mouse 30, according to an embodiment of the invention. The mousepad 20 includes a source loop 22, and the mouse 30

includes a victim loop 32. Both of the loops 22, 32 are internal to their respective housings, and are hidden from view in a standard embodiment. Additionally hidden from view in the standard embodiment are one or more rechargeable batteries 34 in the mouse 30, which are used to power various circuits in the mouse. Briefly, in operation, a current is forced to flow through the source loop 22 of the mousepad 20, which causes current to flow in the victim loop 32 of the mouse 30 by magnetic induction. This current flow, in turn, is used to recharge the batteries 34 of the mouse.

In addition to the mousepad 20 and the mouse 30, the embodiment shown in FIG. 1 also includes a control housing 40. A cable 42, for example a USB cable, couples the control housing 40 to an attached personal computer (PC) 50. In the embodiment where the cable 42 is a USB cable, the control housing may be a USB hub, and include multiple input ports 44 for other devices to connect to the USB bus. As an example, a keyboard may also connect to the USB hub 40. The cable 42 provides a power source through the control housing 40 to the mousepad 20 in order to energize the source loop 22. In this embodiment, the control housing 40 also includes a data receiver 46, such as an IR receiver. The data receiver 46 receives signals from a data transmitter 36 on the mouse 30, such as an IR transmitter, and transmits the received mouse signals (or other signals based on the IR signals received from the mouse IR transmitter) over the USB cable 42 to the computer 50. In this way, the data transmitter 36 on the mouse 30 need only transmit the data signals a very short distance to the data receiver 46 on the control housing 40, and not the entire distance to the computer 50. This allows the data transmitter 36 on the mouse 30 to operate with less power than would be needed to transmit the signals from the mouse directly to the computer 50. In other embodiments, of course, the data receiver

46 can be located on the PC 50 or anywhere else that allows good signal capturing from the mouse transmitter 36.

The power source coming through the cable 42 can be either a DC voltage or an AC voltage. If the cable 42 is a USB cable, then the voltage on the cable is 5 Volts DC, according to the USB standard. The cable 42 could be delivering any type of voltage, but in order to make the constantly changing magnetic field to induce a current flow in the victim loop 32, an alternating current must be supplied to the source loop 22, as discussed below with reference to FIG. 4.

The source loop 22 is formed by one long wire shaped into a spiral coil. The source loop 22 formed in this shape is called a solenoid, and when electric current flows through the source loop, lines of magnetic flux are created within the solenoid. The amount of magnetic flux generated by the source loop 22 is related to a number of factors. A first factor is the amount of current flowing through the source loop 22. Also, the magnetic flux is proportional to the number of turns per unit length of the wire making up the coils in the source loop 22. Additionally, the amount of flux is also based on a magnetic permeability of the material in which the magnetic flux is flowing. Once the overall mechanism for inductively providing power to the mouse 30 has been explained, increasing the effectiveness of the system by maximizing these factors will be examined.

Generally, in operation, the source loop 22 is powered with an alternating current, which creates constantly changing magnetic flux lines (indicating a magnetic field) in the area above and below the mousepad 20. When the mouse 30 is located within the changing magnetic flux lines, a voltage is induced in the victim loop 32. This voltage is fed to a transforming circuit (not shown in FIG. 1) that transforms it into a voltage for use by the mouse 30, such as for charging the batteries 34 in the mouse 30.

FIG. 2 is a cross sectional view of the mouse 30 sitting on the mousepad 20. The source loop 22 and the victim loop 32 can be seen in the cross section. Although in FIG. 2 it appears that there are multiple separate wires in each of the loops 22, 32, the source loop 22 and the victim loop 32 are each made from only 1 strand of wire. When current is applied to the source loop 22, lines of magnetic flux 60 are created inside the coils of wire. As can be seen, the flux lines 60 near the center of the source loop 22 are fairly straight, while those near the edges of the source loop are curved around to the outside of the loop. All of the flux lines from the source loop eventually curve back around the outside of the coil to join with the flux lines extending from the bottom of the mousepad 20, and make a closed loop. For this description, only the portions of the flux lines that are near the mousepad 20 are important for consideration as to their effect on the victim loop 32, because they are the only ones that will interact with the mouse 30 in its normal position resting on the mousepad.

In addition to their unusual shape, the magnetic flux lines 60 have other unusual properties. Because the magnetic flux lines 60 repel one another, the flux lines tend to spread out evenly across the inside of the source loop 22. This is called having a constant flux density across the source loop 22.

Because the mouse 30 is typically much smaller than the mousepad 20, when the mouse is placed on top of the mousepad, much of the magnetic flux lines 60 do not travel through the victim loop 32. Therefore, many of the magnetic flux lines 60 contribute nothing to inducing a voltage in the victim loop, and are simply wasted.

When the mouse 30 is placed within the constantly changing lines of magnetic flux 60, a voltage and current is induced in the victim loop 32 of the mouse. Increasing the amount of magnetic flux 60 also increases the amount of voltage induced in the victim loop 32, so it is advantageous to increase the

magnetic flux as much as possible. As mentioned above, two ways to increase the amount of magnetic flux are to increase the current flowing through the source loop 20 and the number of turns per unit length in the source loop.

Another way to increase the density of the magnetic flux 60 is for the flux
5 to flow through a material having a relatively high magnetic permeability. FIG. 3 shows an embodiment of the invention where both the mousepad 20 and the mouse 30 are formed with areas having a high level of magnetic permeability. The high permeability area of the mousepad 20 is indicated with the reference
10 28, while the high permeability area of the mouse 30 is indicated with the reference 38. Examples of materials having a high magnetic permeability are iron or iron filings, steel, nickel, and cobalt, or combinations of these materials, as well as some more exotic compounds such as silicon iron, and others. These materials can be combined with substrates, such as plastic or foam, or binders
15 such as epoxy to create a material that has high magnetic permeability yet remains easy to work with for manufacturing. As seen in FIG. 3, because the magnetic flux lines 60 can pass through the areas of high level magnetic permeability more easily than they can in the other areas, high density flux lines 70 are present in these areas. Although in this figure both the mousepad 20 and the mouse 30 include the high areas of permeability 28, 38, embodiments of the
20 invention are still operational if, both, or neither the mousepad nor mouse include such areas. If the mouse 30 includes the high areas of permeability 38, then when the mouse is operating normally on top of the mousepad 20, the high density flux lines 70 will move with the mouse and allow more energy transfer from the mousepad than if the high areas of permeability 38 were not included in
25 the mouse.

In addition to being permeable to the magnetic flux, the high areas of permeability 38 may also have properties that make a good transmitter antenna.

Therefore, they may also be formed in conjunction with the data transmitter 36 on the mouse 30 to enhance the transmitter's ability to send the data signals to the receiver.

FIG. 4 is a functional block diagram showing connections and circuit blocks used in the inductive charging system. As before, the cable 42 provides power to the mousepad 20. The cable 42 may be directly attached to the mousepad 20, or may be intermediately connected to the control housing 40 (FIG. 1). The power from the cable 42 is supplied to a primary side power circuit 122, which also has an output to drive the source loop 22. The primary power circuit 122 includes whatever circuitry is necessary to convert the voltage and current provided by the cable 42 into a signal that will provide a constantly changing current for the source loop 22. For example, if the input voltage is a direct current (DC) voltage, the primary power circuit 122 includes a circuit to produce a changing signal, such as an oscillation circuit. An example of such a circuit is a Pulse Width Modulation (PWM) circuit, which can supply the source loop with a constantly changing voltage and current while having a dc voltage as an input. Other oscillating circuits perform similar functions that can be used in place of the PWM circuit. Additionally, the primary power circuit 122 may include voltage matching circuitry, if necessary, to match the voltage supplied to it by the cable 42 with the voltage that is supplied to the source loop 22. For instance, the cable 42 may supply a 120 Volt alternating current (AC) signal. Although the AC portion of that incoming signal may not need to be rectified, it is likely that the 120 volts would be reduced to a lower voltage by the voltage matching circuitry included in the primary power circuit 122.

An additional factor in inductively transferring a voltage is the frequency at which the magnetic flux lines 60 change. So far, the previous factors discussed only how to make more magnetic flux lines 60 (higher current, more

windings, higher permeable materials, etc). An additional consideration in inducing a voltage in two close coils is how fast the magnetic flux lines 60 change. Therefore, the primary power circuit 122 may also include circuitry able to drive the source loop 22 with a rapidly changing (i.e. high frequency) alternating current. A high frequency driver may be included in the primary power circuit 122 even if the cable 42 is carrying an AC signal, if the current is not switching at a high enough frequency for good induction.

Included in the mouse 30 is a secondary power circuit 132, which is used to convert the signal received from the victim loop 32 into one useful to the mouse 30, e.g., to recharge the rechargeable batteries 34. There are fewer variables in designing the secondary power circuit 132 than the primary power circuit 122, because it is known that the source signal coming from the victim loop has an AC voltage. Therefore, if the batteries 34 will be charged with a DC voltage, the secondary power circuit 132 includes an AC to DC converter. A simple converter can be formed of diodes, such as a bridge rectifier, or other more complex circuits could be used. Newer technology in recharging batteries reveals that charging batteries with pulses of current or voltage may have advantages over charging them by traditional constant voltage methods, in terms of reducing memory effects and increasing longevity of the batteries. Therefore, the secondary power circuit 132 may include a pulse charging circuit between the victim loop 32 and the batteries 34.

Load circuitry 136 is also coupled to the battery 34, the secondary power circuit 132, or both of them. Such load circuitry 136 includes the circuits necessary to create the signals transferred back to the PC 50 (FIG. 1), for instance, the X-Y locating circuitry, the circuits to detect the button clicks or mouse wheel rotation, and/or including the transmitter 36 used to transmit the data signals from the mouse 30 to the receiver 46.

The load circuitry 136 of the mouse 30 may require a peak current draw of about 50mA, or some other number. This peak current need may exceed the instantaneous capacity of the effective current of the signal from the source loop 32. This is acceptable, because there will often be times when the mouse 30 uses
5 no power, for instance at times when the user is not operating the mouse and it has shut down. During these non-operational times, if there is still a power connection via the cable 42, the mouse 30 will continue to charge its rechargeable batteries 34. If, for instance the useable current from the secondary power circuit 132 is about 5mA, there must be adequate time to charge the batteries 34 to ensure there is enough stored power to drive the load circuitry 136. Provided the source loop 32 is energized for long periods of time while the mouse is being unused, then the average power output by the secondary power circuit 132 should be more than the average power requirements of the mouse 30, in normal operation.

As power requirements for the load circuitry 136 in a mouse 30 are reduced by new methods and standards, it may be that the induced signal from the victim loop 32 is able to completely power the load circuitry 136. If this were always the case, then the batteries 34 could be eliminated from the mouse 30, or, in alternative embodiments, the secondary power circuit 132 could choose to
20 power the load circuitry from either the signal received from the victim loop 32, the batteries 34, or a combination of both of them. For example, if the signal from the victim loop 32 was 10 mA, and the load circuitry 136 required only 6 mA, then the secondary power circuit 132 could supply the first 6 mA to the load circuitry 136 and route the remaining 4 mA to recharge the batteries 34. As
25 mentioned above, if the signal generated by the victim loop 32 is always greater than the highest instantaneous power requirements of the load circuitry 136, then the batteries 34 could be eliminated from the mouse 30 entirely.

If the mouse 30 does include batteries 34, then once the batteries have reached an acceptable level of recharging, the mouse may be removed from the area near the source loop 22, and the mouse will continue to work, using its stored charge in the batteries to supply power to the mouse. When the batteries
5 discharge, either from use or simply from slowly discharging themselves over time, the mouse 30 will need to be returned to the mousepad 20 for recharging.

Nothing prevents embodiments of the invention from being used in conjunction with a docking cradle that is also able to recharge the batteries 34 of the mouse. Such a system is shown in FIG. 5, which shows a docking cradle 90
10 shaped to accept the mouse 30 within it. The docking cradle 90 may also have a source loop 22 (not shown because internal) and is able to inductively provide power to the mouse 30, or it may have conventional charging electrodes. In the latter case, the mouse 30 would include a matching set of electrodes connected to a circuit that recharges the batteries 34 of the mouse. In either case, the docking
15 cradle 90 would have to be able to provide more power to the mouse than the mousepad 20; otherwise the user would simply choose to power the mouse during normal use with the mousepad, because it is more convenient. If the source loop 22 within the docking cradle 90 created the same overall magnetic flux 60 as the source loop 22 in the mousepad 20, then the docking cradle 90 would transfer
20 more power to the mouse than the mousepad because more magnetic flux would contact the victim loop 32 in the mouse 30. This is because presumably the docking cradle 90 would be shaped to exactly match the size of the victim loop 32 of the mouse 30, and none of the magnetic flux 60 would escape around the sides of the mouse, as was seen in FIG. 2.

FIG. 6A shows one embodiment of layout of the source loop 22 in relation
25 to the mousepad 20. In this embodiment, the source loop 22 is formed around the perimeter of the mousepad 20. Although in this figure the source loop 22 is

shown in a generally rectangular shape, a more circular shape could also be used. The more circular shape would make a more uniform distribution of the magnetic flux lines 60 (not shown in FIG. 6A), but a larger portion of the mousepad 22, near the corners, would have areas of very little magnetic flux. In such a case, the surface of the mousepad 20 itself may have printing or some other indication of where the user should best place the mouse 30 to maximize the inductive power from the mousepad.

FIG. 6B shows another example of how the source loop 22 could be laid out in the mousepad 20. In this example, a number of separate source loops, 22A, 22B, 22C and 22D are used. If each of these separate source loops can generate as many magnetic flux lines 60 as the source loop 22 of FIG. 6A, then more magnetic flux is generated in this type of layout, which will result in a greater transfer of induced voltage in the mouse 30. In the example shown in FIG. 6B, the primary power circuit 122 (FIG. 4) would need to be modified to drive all of the source loops 22A-22D.

FIG. 7 shows an example layout of the victim loop 32 within the mouse 30. Similar to that of FIG. 6A, the victim loop in this embodiment is formed around the perimeter of the mouse 30, although nothing limits how the victim loop 32 can be situated within the mouse. For instance there may be an advantage to including multiple victim loops 32 arranged within the mouse, similar to the arrangement shown for the source loops 22A-22D in FIG. 6B. Generally, though, because it is likely that the mouse 30 will always be completely within the magnetic flux lines 60 generated by the mousepad 20, there should not be an advantage to making multiple victim loops 22 within the mouse 30.

FIG. 8 shows an alternative embodiment for the inductive charging system. This figure shows how the source loops 22 and the victim loops 32 can be implemented on nearly the same plane as one another. In application, sides

23 of the mousepad 20 can be made to extend vertically to house the victim coils 22. This creates a depression area 25 near the center of the mousepad, in which the mouse 30 sits. In this configuration, the victim loops 32 are almost completely inside the source loops 22, which increases the effective ability to generate a voltage in the source loop 32. Although this embodiment shows the sides 23 extending many times the distance of the height of the depression area 25, the actual implementation may range from no increased side elevation, to one where the sides of the mousepad 20 extend beyond the height of the mouse 30 during normal operation. The actual implementation may be empirically determined, and consumer considerations may also be factored into the decision of how high to make the sides 23. One such consideration is the position of a user's hand required to hold the mouse 30 over the side 23 that is closest to the user. If the sides 23 are relatively high, this position may be uncomfortable for the user of the mouse 30.

Implementation of the inductive charging system is straightforward and intuitive once the details of the invention as described above are known. As always, implementation of the invention is left to the system designer. The mousepad may be implemented in any way, with any circuits, and from any material or combination of materials, as long as it is able to generate the magnetic flux lines to interact with the mouse. Indeed, although embodiments of the invention were described using an example of a mousepad, there is really no requirement that it be a mousepad at all. For instance, the circuitry necessary to generate the magnetic flux may simply be incorporated in a pad on which a standard mousepad rests. Or, the circuitry may be actually embedded into a desk or other support that is used to hold the mouse. Most likely, however, mousepads including the necessary circuitry will be the easiest to distribute to a user of the system.

Similarly, the mouse 30 can be implemented in any way, with any circuits, and from any material or combination of materials, as long as it is able to convert the magnetic flux lines sensed by the mouse into a signal able to recharge batteries within the mouse, or to drive the circuitry of the mouse
5 directly.

Thus, although particular embodiments for an inductive recharging system for a peripheral device have been discussed, it is not intended that such specific references be considered as limitations upon the scope of this invention, but rather the scope is determined by the following claims and their equivalents.

10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
2216
2217
2218